


MIO MIX 404FXM

6-CHANNEL PROFESSIONAL AUDIO MIXER WITH MEDIA PLAYER, BT & 24-BIT DIGITAL MULTI-EFFECT

MioMix 404FXM is a 6-channel mixer with USB player and digital multi-effect ideal for small home recording, live gigs and podcasting applications that require professional quality level and maximum portability. 4 Mic inputs are equipped with noise-less preamps that accepts all main sound sources, such as condenser microphones - thanks to the +48V Phantom Power, dynamic mics, line and high-impedance inputs (guitars, basses, etc.). The stereo line input allow you to connect keyboards, CD players, DJ consoles, tablets, smartphones, etc. The USB & BT player accepts WAV, MP3, WMA and FLAC format audio files, as well as wireless audio streaming (BT). It also records your gig in MP3 format (48kHz/16bit @ 128Kbps). The 24-bit/48kHz digital effect with 16 commonly used presets (Hall/Room/Plate Reverb, Delay, Echo, Chorus, etc.) and TAP-Tempo function let you improve your performance and adjust up to two parameters of each effect. An indispensable and reliable tool for all small audio applications.



PRODUCT DETAILS

KEY FEATURES

6 Total Channels

4 Mic/Line channels with noiseless preamp, combo connector, Hi-Z input for guitars, +48V Phantom Power, Peak Indicator

1 Stereo Line Channel with ¼" Jack inputs, +4/-10dB Pad Adapter and Peak Indicator

USB Media Player and Recorder (WAV, MP3, WMA, FLAC and BT wireless audio streaming)

2-Band EQ for channels 1 to 4

24-bit/48kHz 16-Preset Digital Effect with TAP-Tempo and up to 2 adjustable Parameters

Media Player output level control

Headphone monitor out with level control

XLR Main Outputs with Master Level Control

Stereo 6-Led VU Meter Bar

Rugged and Lightweight Metal Case for Maximum Flexibility and Portability

SPECIFICATIONS

| | |
|------------------------------|---|
| Input Connections | Balanced XLR/Jack Combo (Channel 1-4), Balanced ¼" Jack (Channel 5-6) |
| Output Connection | Balanced XLR (Main Out L-R), Stereo ¼" Jack (Phones), Stereo RCA (Rec Out) |
| Channel 1-4 Functions | +48V Phantom Power, Impedance switch (Line/Hi-Z), 2-Band EQ (80Hz/12kHz +/-15dB), Effect Send Level, Pan Position, Channel Volume, Peak Led Indicator |
| Channel 5-6 Functions | Impedance switch (+4/-10dB), Pan Position, Channel Volume, Peak Led Indicator |
| USB Player Buttons | Up/Rewind, Down/Forward, Play/Pause/Enter, Menu |
| USB Player Functions | BT streaming, Music Player, Audio Recording, EQ-Curve Selection |
| USB Drive Format | FAT32 format – max 64GByte |
| Player File Formats | WAV, MP3, WMA, FLAC e streaming audio wireless BT |
| Recorder File Format | MP3 (48kHz/16bit @ 128Kbps) |
| Digital Effect | 24-bit Sigma-Delta, 256-times oversampling, 48kHz sampling rate |
| Level Meter | 2x6 LED Meter |
| Max Output Level | 3 Vrms |
| Frequency Response | +/-0.5dB, 20Hz-20kHz |
| Dynamic Range | 102dB |
| THD+N @ 1kHz | =0.003% |
| Stereo Crosstalk | 92dB |
| Power Requirements | DC 5V, 1A |
| Power Consumption | Max. 2.5W |
| Size (WxDxH) | 274 x 165 x 66 mm |
| Packing Size (WxDxH) | 390 x 207 x 87 mm |
| Net Weight | 1.5 kg |
| Gross Weight | 1.65kg |