

WF-V21PPB

DUAL VHF PLUG AND PLAY WIRELESS MICROPHONE WITH 2 BODYPACK AND HEADSET MICS (205.75 MHZ - 209.8 MHZ)

WF-V21 is the answer to all those who need a reliable, high-quality sound, and easy to use set of wireless microphones. Ideal in educational, Portable Sound, Public Address, and DJ contexts, the WF-V21 impresses with its brilliant and warm sound, thanks to the quality of components and the capsule designed for all application.



PRODUCT DETAILS

KEY FEATURES

VHF Transmission with SMD Technology

2 available Pairs of Frequencies in VHF Band

Simple user Interface for plug and play setup

30m ideal distance (without obstacles)

2 Strong yet lightweight bodypack

Professional and Lightweight Headsets with high-sensibility dynamic cardioid capsules

SPECIFICATIONS

| | |
|---|--|
| Carrier Frequency | VHF 200 - 215.3 MHz |
| Operating Frequencies | 205.75 MHz - 209.8 MHz |
| Frequency Stabilization | Automatic calibration |
| Dynamic Range | > 90dB |
| Total Harmonic Distortion | < 0.5% |
| Frequency Response | 40Hz - 16kHz / ± 3 dB |
| Packing Dimensions (WxHxD) | 436 x 104 x 324 mm |
| Packing Gross Weight | 2.0 kg |
| Receiver Power Supply | DC12V, 500mA |
| Receiver Consumption | < 4W |
| Signal/Noise Ratio | > 95dB |
| Receiving Sensitivity | 10dBuV |
| De-Emphasis | 75uS |
| Audio Output Level | Balanced 400mV; Unbalanced 400mV |
| Receiver Size (WxHxD) | 211 x 43 x 115 mm (antennas not incl.) |
| Antenna Length | 110 mm (min.) 430 mm (max.) |
| Net Weight | 0.295 kg |
| Transmitter Power | 10mW |
| Modulation Type | FM |
| Deviation | 37KHz |
| Battery Voltage | 3V (2x1.5V AA-Type Batteries) |
| Continuous Using | 7 hours |
| Pocket Trans. Dimensions (WxHxD) | 62 x 103 x 30 mm |
| Antenna (W/DxH) | $\varnothing 3$ x 9 mm |
| Pocket Transmitter Net Weight | 0.132 kg (batteries included) |