

WF-V21HHA

## DUAL VHF PLUG AND PLAY WIRELESS MICROPHONE WITH 2 HANDHELD MICS (213.0 MHZ - 215.5 MHZ)

WF-V21 is the answer to all those who need a reliable, high-quality sound, and easy to use set of wireless microphones. Ideal in educational, Portable Sound, Public Address, and DJ contexts, the WF-V21 impresses with its brilliant and warm sound, thanks to the quality of components and the capsule designed for all application.



## PRODUCT DETAILS

### KEY FEATURES

VHF Transmission with SMD Technology

2 available Pairs of Frequencies in VHF Band

Simple user Interface for plug and play setup

30m ideal distance (without obstacles)

2 Handheld microphones with high-quality dynamic cardioid capsules

## SPECIFICATIONS

<b>Carrier Frequency</b>	VHF 200 - 215.3 MHz
<b>Operating Frequencies</b>	213.0 MHz - 215.5 MHz
<b>Frequency Stabilization</b>	Automatic calibration
<b>Dynamic Range</b>	> 90dB
<b>Total Harmonic Distortion</b>	< 0.5%
<b>Frequency Response</b>	40Hz - 16kHz / $\pm 3$ dB
<b>Packing Dimensions (WxHxD)</b>	436 x 104 x 324 mm
<b>Packing Gross Weight</b>	2.0 kg
<b>Receiver Power Supply</b>	DC12V, 500mA
<b>Receiver Consumption</b>	< 4W
<b>Signal/Noise Ratio</b>	> 95dB
<b>Receiving Sensitivity</b>	10dBuV
<b>De-Emphasis</b>	75uS
<b>Audio Output Level</b>	Balanced 400mV; Unbalanced 400mV
<b>Receiver Size (WxHxD)</b>	211 x 43 x 115 mm (antennas not incl.)
<b>Antenna Length</b>	110 mm (min.) 430 mm (max.)
<b>Net Weight</b>	0.295 kg
<b>Transmitter Power</b>	10mW
<b>Modulation Type</b>	FM
<b>Deviation</b>	37KHz
<b>Battery Voltage</b>	3V (2x1.5V AA-Type Batteries)
<b>Continuous Using</b>	7 hours
<b>Hand-held Mic. Size (W/DxH)</b>	$\varnothing 33$ (min) - $\varnothing 48$ (max) x 240 mm
<b>Hand-held Mic. Net Weight</b>	0.218 kg (batteries included)